

BANK 56		BANK 57		BANK 58		BANK 59		BANK 60		BANK 61		BANK 62		BANK 63					
1C00h	Core Registers	1C80h	Core Registers	1D00h	Core Registers	1D80h	Core Registers	1E00h	Core Registers	1E80h	Core Registers	1F00h	Core Registers	1F80h	Core Registers				
1C0Bh	Unimplemented Read as '0'	1C8Bh	Unimplemented Read as '0'	1D0Bh	Unimplemented Read as '0'	1D8Bh	Unimplemented Read as '0'	1E0Bh	See Figure 9-12 for register mapping details	1E8Bh	See Figure 9-13 for register mapping details	1F0Bh	Unimplemented Read as '0'	1F8Bh	Unimplemented Read as '0'				
1C0Ch		1C8Ch		NVMADRL		1D0Ch		ADLTHL		1D8Ch		RA0PPS		1E0Ch		1E8Ch	1F0Ch	UMTOAP	1F8Ch
		1C8Dh		NVMADRH		1D0Dh		ADLTHH		1D8Dh		RA1PPS					1F0Dh	UMTOAL	
		1C8Eh		NVMDATL		1D0Eh		ADUTHL		1D8Eh		RA2PPS					1F0Eh	UMTOAH	
		1C8Fh		NVMDATH		1D0Fh		ADUTHH		1D8Fh		—					1F0Fh	—	
		1C90h		NVMCON1		1D10h		ADERRL		1D90h		RA4PPS							
		1C91h		NVMCON2		1D11h		ADERRH		1D91h		RA5PPS							
		1C92h		SCANLADRL		1D12h		ADSTPTL		1D92h		—							
		1C93h		SCANLADRH		1D13h		ADSTPTH		1D93h		—							
		1C94h		—		1D14h		ADFLTRL		1D94h		—							
		1C95h		SCANHADRL		1D15h		ADFLTRH		1D95h		—							
		1C96h		SCANHADRH		1D16h		ADACCL		1D96h		—							
		1C97h		—		1D17h		ADACCH		1D97h		—							
		1C98h		SCANCON		1D18h		ADACCU		1D98h		RB4PPS ⁽¹⁾							
		1C99h		SCANDTI		1D19h		ADCNT		1D99h		RB5PPS ⁽¹⁾							
		1C9Ah		CRCDATAL		1D1Ah		ADRPT		1D9Ah		RB6PPS ⁽¹⁾							
		1C9Bh		CRCDATAH		1D1Bh		ADPREVL		1D9Bh		RB7PPS ⁽¹⁾							
		1C9Ch		CRCDATAU		1D1Ch		ADPREVH		1D9Ch		RC0PPS ⁽²⁾							
		1C9Dh		CRCDATAT		1D1Dh		ADRESL		1D9Dh		RC1PPS ⁽²⁾							
		1C9Eh		CRCOUTL		1D1Eh		ADRESH		1D9Eh		RC2PPS ⁽²⁾							
		1C9Fh		CRCOUTH		1D1Fh		ADPCH		1D9Fh		RC3PPS ⁽²⁾							
		1CA0h		CRCOUTU		1D20h		ADNCH		1DA0h		RC4PPS ⁽²⁾							
		1CA1h		CRCOUTT		1D21h		ADACQL		1DA1h		RC5PPS ⁽²⁾							
	1CA2h	CRCCON0	1D22h	ADACQH	1DA2h	RC6PPS ⁽¹⁾													
	1CA3h	CRCCON1	1D23h	ADCAP	1DA3h	RC7PPS ⁽¹⁾													
	1CA4h	CRCCON2	1D24h	ADPREL	1DA4h	Unimplemented Read as '0'													
	1CA5h	Unimplemented Read as '0'	1D25h	ADPREH															
			1D26h	ADCON0															
			1D27h	ADCON1															
			1D28h	ADCON2															
			1D29h	ADCON3															
			1D2Ah	ADSTAT															
			1D2Bh	ADREF															
			1D2Ch	ADACT															
			1DCDh	ADCLK															
			1D2Eh	ADCG1A															
		1D2Fh	ADCG1B ⁽¹⁾																
		1D30h	ADCG1C ⁽²⁾																
		1D31h	Unimplemented Read as '0'																
1C6Fh	Common RAM (Accesses 70h-7Fh)	1CFEh	Common RAM (Accesses 70h-7Fh)	1D6Fh	Common RAM (Accesses 70h-7Fh)	1DEFh	Common RAM (Accesses 70h-7Fh)	1E6Fh	Common RAM (Accesses 70h-7Fh)	1EEFh	Common RAM (Accesses 70h-7Fh)	1F6Fh	Common RAM (Accesses 70h-7Fh)	1FE3h	Common RAM (Accesses 70h-7Fh)				
1C70h		1CF0h		1D70h		1DF0h		1E70h		1EF0h		1F70h		1FF0h					
1C7Fh		1CFFh		1D7Fh		1DFFh		1E7Fh		1EFFh		1F7Fh		1FFFh					

Note: 1. Available on 20-pin devices only
2. Available on 14/20-pin devices

Legend:

■ Unimplemented data memory locations, read as '0'