


BANK 8		BANK 9		BANK 10		BANK 11		BANK 12		BANK 13		BANK 14		BANK 15									
400h	Core Registers	480h	Core Registers	500h	Core Registers	580h	Core Registers	600h	Core Registers	680h	Core Registers	700h	Core Registers	780h	Core Registers								
40Bh		48Bh		50Bh		58Bh		60Bh		68Bh		70Bh		78Bh									
40Ch	CCPR1L	48Ch	PWM1ERS	50Ch	CLBCON	58Ch	PWM2ERS	60Ch	—	68Ch	CLCnCON	70Ch	RC1REG	78Ch	SSP1BUF								
40Dh	CCPR1H	48Dh	PWM1CLK	50Dh	CLBSWINU	58Dh	PWM2CLK	60Dh	—	68Dh	CLCnPOL	70Dh	TX1REG	78Dh	SSP1ADD								
40Eh	CCP1CON	48Eh	PWM1LDS	50Eh	CLBSWINH	58Eh	PWM2LDS	60Eh	—	68Eh	CLCnSEL0	70Eh	SP1BRGL	78Eh	SSP1MSK								
40Fh	CCP1CAP	48Fh	PWM1PRL	50Fh	CLBSWINM	58Fh	PWM2PRL	60Fh	—	68Fh	CLCnSEL1	70Fh	SP1BRGH	78Fh	SSP1STAT								
410h	CCPR2L	490h	PWM1PRH	510h	CLBSWINL	590h	PWM2PRH	610h	—	690h	CLCnSEL2	710h	RC1STA	790h	SSP1CON1								
411h	CCPR2H	491h	PWM1CPRE	511h	—	591h	PWM2CPRE	611h	—	691h	CLCnSEL3	711h	TX1STA	791h	SSP1CON2								
412h	CCP2CON	492h	PWM1PIPOS	512h	—	592h	PWM2PIPOS	612h	—	692h	CLCnGLS0	712h	BAUD1CON	792h	SSP1CON3								
413h	CCP2CAP	493h	PWM1GIR	513h	—	593h	PWM2GIR	613h	—	693h	CLCnGLS1	713h	—	793h	Unimplemented Read as '0'								
414h	—	494h	PWM1GIE	514h	—	594h	PWM2GIE	614h	—	694h	CLCnGLS2	714h	—										
415h	—	495h	PWM1CON	515h	CLBCLK	595h	PWM2CON	615h	—	695h	CLCnGLS3	715h	—										
416h	—	496h	PWM1S1CFG	516h	CLBSWOUTH	596h	PWM2S1CFG	616h	—	696h	CLCSELECT	716h	RC2REG										
417h	—	497h	PWM1S1P1L	517h	CLBSWOUTL	597h	PWM2S1P1L	617h	—	697h	CLCDATA	717h	TX2REG										
418h	—	498h	PWM1S1P1H	518h	CLBDEBUG0	598h	PWM2S1P1H	618h	—	698h	—	718h	SP2BRGL										
419h	—	499h	PWM1S1P2L	519h	—	599h	PWM2S1P2L	619h	—	699h	—	719h	SP2BRGH										
41Ah	—	49Ah	PWM1S1P2H	51Ah	—	59Ah	PWM2S1P2H	61Ah	—	69Ah	—	71Ah	RC2STA										
41Bh	—	49Bh	—	51Bh	—	59Bh	—	61Bh	—	69Bh	—	71Bh	TX2STA										
41Ch	—	49Ch	—	51Ch	—	59Ch	—	61Ch	—	69Ch	—	71Ch	BAUD2CON										
41Dh	—	49Dh	—	51Dh	—	59Dh	—	61Dh	—	69Dh	—	71Dh	—										
41Eh	—	49Eh	PWMLOAD	51Eh	—	59Eh	—	61Eh	—	69Eh	—	71Eh	—										
41Fh	CCPTMRS0	49Fh	PWMEN	51Fh	—	59Fh	—	61Fh	—	69Fh	—	71Fh	—										
420h	General Purpose Registers 80 Bytes ⁽¹⁾	4A0h	General Purpose Registers 80 Bytes ⁽¹⁾	520h	General Purpose Registers 80 Bytes ⁽¹⁾	5A0h	General Purpose Registers 80 Bytes ⁽¹⁾	620h	General Purpose Registers 48 Bytes ⁽¹⁾	6A0h	Unimplemented Read as '0'	720h	Unimplemented Read as '0'			7Eh	Unimplemented Read as '0'						
64Fh		Unimplemented Read as '0'		650h		Unimplemented Read as '0'																	
66Fh				Common RAM (Accesses 70h-7Fh)				670h	Common RAM (Accesses 70h-7Fh)	67Fh		Common RAM (Accesses 70h-7Fh)											
470h		Common RAM (Accesses 70h-7Fh)				4F0h		Common RAM (Accesses 70h-7Fh)		570h				Common RAM (Accesses 70h-7Fh)	5F0h	Common RAM (Accesses 70h-7Fh)		670h	Common RAM (Accesses 70h-7Fh)	770h	Common RAM (Accesses 70h-7Fh)	7F0h	Common RAM (Accesses 70h-7Fh)
47Fh						Common RAM (Accesses 70h-7Fh)				4Fh					Common RAM (Accesses 70h-7Fh)			57Fh		Common RAM (Accesses 70h-7Fh)		5Fh	

Note: 1. Not available on PIC16F13224/44 devices

Legend:

 Unimplemented data memory locations, read as '0'