

BANK 16		BANK 17		BANK 18		BANK 19		BANK 20		BANK 21		BANK 22		BANK 23	
800h	Core Registers	880h	Core Registers	900h	Core Registers	980h	Core Registers	A00h	Core Registers	A80h	Core Registers	B00h	Core Registers	B80h	Core Registers
80Bh		88Bh		90Bh		98Bh		A0Bh		A8Bh		B0Bh		B8Bh	
80Ch	CM1CON0	88Ch	DAC1CON0	90Ch	OPA1CON0	98Ch	—	A0Ch	—	A8Ch	OPA4CON0 ⁽¹⁾	B0Ch	OPA3CON0	B8Ch	—
80Dh	CM1CON1	88Dh	DAC1DATL	90Dh	OPA1CON1	98Dh	—	A0Dh	—	A8Dh	OPA4CON2 ⁽¹⁾	B0Dh	OPA3CON2	B8Dh	—
80Eh	CM1NCH	88Eh	DAC1DATH	90Eh	OPA1CON2	98Eh	—	A0Eh	—	A8Eh	OPA4CON3 ⁽¹⁾	B0Eh	OPA3CON3	B8Eh	—
80Fh	CM1PCH	88Fh	—	90Fh	OPA1CON3	98Fh	—	A0Fh	—	A8Fh	OPA4OFFSET ⁽¹⁾	B0Fh	OPA3OFFSET	B8Fh	—
810h	CMLP1CON0	890h	DAC2CON0	910h	OPA1OFFSET	990h	—	A10h	—	A90h	OPA4CON4 ⁽¹⁾	B10h	OPA3CON4	B90h	—
811h	CMLP1CON1	891h	DAC2DATL	911h	OPA1CON4	991h	—	A11h	—	A91h	—	B11h	—	B91h	—
812h	CMLP1NCH	892h	DAC2DATH	912h	OPA2CON0	992h	—	A12h	—	A92h	—	B12h	—	B92h	—
813h	CMLP1PCH	893h	—	913h	OPA2CON1	993h	—	A13h	—	A93h	—	B13h	—	B93h	—
814h	—	894h	—	914h	OPA2CON2	994h	—	A14h	—	A94h	—	B14h	—	B94h	—
815h	—	895h	—	915h	OPA2CON3	995h	—	A15h	—	A95h	—	B15h	—	B95h	—
816h	—	896h	—	916h	OPA2OFFSET	996h	—	A16h	—	A96h	—	B16h	—	B96h	—
817h	—	897h	—	917h	OPA2CON4	997h	—	A17h	—	A97h	—	B17h	—	B97h	—
818h	—	898h	—	918h	—	998h	—	A18h	—	A98h	—	B18h	—	B98h	—
819h	—	899h	—	919h	—	999h	—	A19h	—	A99h	—	B19h	—	B99h	—
81Ah	—	89Ah	—	91Ah	—	99Ah	—	A1Ah	—	A9Ah	—	B1Ah	—	B9Ah	—
81Bh	—	89Bh	—	91Bh	—	99Bh	—	A1Bh	—	A9Bh	—	B1Bh	—	B9Bh	—
81Ch	—	89Ch	—	91Ch	—	99Ch	—	A1Ch	—	A9Ch	—	B1Ch	—	B9Ch	—
81Dh	—	89Dh	—	91Dh	—	99Dh	—	A1Dh	—	A9Dh	—	B1Dh	—	B9Dh	—
81Eh	—	89Eh	—	91Eh	—	99Eh	—	A1Eh	—	A9Eh	—	B1Eh	—	B9Eh	—
81Fh	CMOUT	89Fh	—	91Fh	—	99Fh	—	A1Fh	—	A9Fh	—	B1Fh	—	B9Fh	—
820h		8A0h		920h		9A0h		A20h		AA0h		B20h		BA0h	
	General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes		General Purpose Registers 80 Bytes
86Fh		8EFh		96Fh		9EFh		A6Fh		AEFh		B6Fh		BEFh	
870h	Common RAM (Accesses 70h-7Fh)	8F0h	Common RAM (Accesses 70h-7Fh)	970h	Common RAM (Accesses 70h-7Fh)	9F0h	Common RAM (Accesses 70h-7Fh)	A70h	Common RAM (Accesses 70h-7Fh)	AF0h	Common RAM (Accesses 70h-7Fh)	B70h	Common RAM (Accesses 70h-7Fh)	BF0h	Common RAM (Accesses 70h-7Fh)
87Fh		8FFh		97Fh		9FFh		A7Fh		AFFh		B7Fh		BFFh	

Note: 1. Available on 40-pin devices only

Legend:

Unimplemented data memory locations, read as '0'