

**BANK 60**

1E00h	Core Registers	1E3Ah	Unimplemented Read as '0'
1E0Bh		1E3Ch	
1E0Ch	PPSLOCK	1E3Dh	CLCIN0PPS
1E0Dh	INTPPS	1E3Eh	CLCIN1PPS
1E0Eh	TOCKIPPS	1E3Fh	CLCIN2PPS
1E0Fh	T1CKIPPS	1E40h	CLCIN3PPS
1E10h	T1GPPS	1E41h	DT1PPS
1E11h	T3CKIPPS	1E42h	RX1PPS
1E12h	T3GPPS	1E43h	DT2PPS
1E13h	Unimplemented Read as '0'	1E44h	RX2PPS
1E18h		1E45h	—
1E19h	T2INPPS	1E46h	—
1E1Ah	T4INPPS	1E47h	SSP1CLKPPS
1E1Bh	T6INPPS	1E48h	SSP1DATPPS
1E1Ch	—	1E49h	SSP1SSPPS
1E1Dh	—	1E4Ah	SSP2CLKPPS
1E1Eh	CCP1PPS	1E4Bh	SSP2DATPPS
1E1Fh	CCP2PPS	1E4Ch	SSP2SSPPS
1E20h	Unimplemented Read as '0'	1E4Dh	Unimplemented Read as '0'
1E23h		1E4Fh	
1E24h	PWMIN0PPS	1E50h	ADACTPPS
1E25h	PWMIN1PPS	Unimplemented Read as '0'	
1E26h	PWM1ERSPPS		
1E27h	PWM2ERSPPS		
1E28h	PWM3ERSPPS		
1E29h	PWM4ERSPPS		
1E2Ah	Unimplemented Read as '0'		
1E38h			1E6Fh
1E39h	CWG1PPS	1E70h	Common RAM (Accesses 70h-7Fh)
		1E7Fh	

Legend:  Unimplemented data memory locations, read as '0'