

BANK 16		BANK 17		BANK 18		BANK 19		BANK 20		BANK 21		BANK 22		BANK 23	
800h	Core Registers	880h	Core Registers	900h	Core Registers	980h	Core Registers	A00h	Core Registers	A80h	Core Registers	B00h	Core Registers	B80h	Core Registers
80Bh		88Bh		90Bh		98Bh		A0Bh		A8Bh		B0Bh		B8Bh	
80Ch	CM1CON0	88Ch	DAC1CON0	90Ch	OPA1CON0	98Ch	PWM3ERS	A0Ch	PWM4ERS	A8Ch	—	B0Ch	—	B8Ch	—
80Dh	CM1CON1	88Dh	DAC1DATL	90Dh	OPA1CON1	98Dh	PWM3CLK	A0Dh	PWM4CLK	A8Dh	—	B0Dh	—	B8Dh	—
80Eh	CM1NCH	88Eh	—	90Eh	OPA1CON2	98Eh	PWM3LDS	A0Eh	PWM4LDS	A8Eh	—	B0Eh	—	B8Eh	—
80Fh	CM1PCH	88Fh	—	90Fh	OPA1CON3	98Fh	PWM3PRL	A0Fh	PWM4PRL	A8Fh	—	B0Fh	—	B8Fh	—
810h	CM2CON0	890h	DAC2CON0	910h	OPA1HWC	990h	PWM3PRH	A10h	PWM4PRH	A90h	—	B10h	—	B90h	—
811h	CM2CON1	891h	DAC2DATL	911h	OPA1OFFSET	991h	PWM3CPRE	A11h	PWM4CPRE	A91h	—	B11h	—	B91h	—
812h	CM2NCH	892h	—	912h	OPA1ORS	992h	PWM3PIPOS	A12h	PWM4PIPOS	A92h	—	B12h	—	B92h	—
813h	CM2PCH	893h	—	913h	—	993h	PWM3GIR	A13h	PWM4GIR	A93h	—	B13h	—	B93h	—
814h	—	894h	—	914h	—	994h	PWM3GIE	A14h	PWM4GIE	A94h	—	B14h	—	B94h	—
815h	—	895h	—	915h	—	995h	PWM3CON	A15h	PWM4CON	A95h	—	B15h	—	B95h	—
816h	—	896h	—	916h	—	996h	PWM3S1CFG	A16h	PWM4S1CFG	A96h	—	B16h	—	B96h	—
817h	—	897h	—	917h	—	997h	PWM3S1P1L	A17h	PWM4S1P1L	A97h	—	B17h	—	B97h	—
818h	—	898h	—	918h	—	998h	PWM3S1P1H	A18h	PWM4S1P1H	A98h	—	B18h	—	B98h	—
819h	—	899h	—	919h	—	999h	PWM3S1P2L	A19h	PWM4S1P2L	A99h	—	B19h	—	B99h	—
81Ah	—	89Ah	—	91Ah	—	99Ah	PWM3S1P2H	A1Ah	PWM4S1P2H	A9Ah	—	B1Ah	—	B9Ah	—
81Bh	—	89Bh	—	91Bh	—	99Bh	—	A1Bh	—	A9Bh	—	B1Bh	—	B9Bh	—
81Ch	—	89Ch	—	91Ch	—	99Ch	—	A1Ch	—	A9Ch	—	B1Ch	—	B9Ch	—
81Dh	—	89Dh	—	91Dh	—	99Dh	—	A1Dh	—	A9Dh	—	B1Dh	—	B9Dh	—
81Eh	—	89Eh	—	91Eh	—	99Eh	—	A1Eh	—	A9Eh	—	B1Eh	—	B9Eh	—
81Fh	CMOUT	89Fh	—	91Fh	—	99Fh	—	A1Fh	—	A9Fh	—	B1Fh	—	B9Fh	—
820h	Unimplemented Read as '0'	8A0h	Unimplemented Read as '0'	920h	Unimplemented Read as '0'	9A0h	Unimplemented Read as '0'	A20h	Unimplemented Read as '0'	AA0h	Unimplemented Read as '0'	B20h	Unimplemented Read as '0'	BA0h	Unimplemented Read as '0'
86Fh		8EFh		96Fh		9EFh		A6Fh		AEFh		B6Fh		BEFh	
870h	Common RAM (Accesses 70h-7Fh)	8F0h	Common RAM (Accesses 70h-7Fh)	970h	Common RAM (Accesses 70h-7Fh)	9F0h	Common RAM (Accesses 70h-7Fh)	A70h	Common RAM (Accesses 70h-7Fh)	AF0h	Common RAM (Accesses 70h-7Fh)	B70h	Common RAM (Accesses 70h-7Fh)	BF0h	Common RAM (Accesses 70h-7Fh)
87Fh		8FFh		97Fh		9FFh		A7Fh		AFh		B7Fh		BFh	

Legend:

Unimplemented data memory locations, read as '0'