

Bit	7	6	5	4	3	2	1	0
					SEQSELn[3:0]			
Access					R/W	R/W	R/W	R/W
Reset					0	0	0	0

Bits 3:0 – SEQSELn[3:0]: Sequential Selection bits

The bits in SEQSELn select the sequential configuration for LUT[2n] and LUT[2n+1].

Value	Name	Description
0x0	DISABLE	Sequential logic is disabled
0x1	DFF	D flip flop
0x2	JK	JK flip flop
0x3	LATCH	D latch
0x4	RS	RS latch
Other	-	Reserved