Address	Device	
	PIC18Fx6Q83	PIC18Fx7Q83
00 0000h		
to		
00 3FFFh		
00 4000h	Program Flash	
to	Memory	Program Flash
00 7FFFh	(32 KW) ⁽¹⁾	Memory
00 8000h		(64 KW) ⁽¹⁾
to		(011111)
00 FFFFh		
01 0000h		
to		
01 FFFFh	Not	
02 0000h	Present ⁽²⁾	Not
to		Present ⁽²⁾
1F FFFFh		1 1000111
20 0000h		
to	User IDs (32 Words) ⁽³⁾	
20 001Fh 20 0020h		
to	Reserved	
2B FFFFh	rteserveu	
2C 0000h		
to	Device Information Area (DIA)(3)(5)	
2C 00FFh		
2C 0100h		
to	Reserved	
2F FFFFh		
30 0000h	Configuration Mondo (3)	
to 30 0022h	Configuration Words (3)	
30 0022h		
to	Reserved	
37 FFFFh		
38 0000h		
to	Data EEPROM (1024 Bytes)	
38 03FFh		
38 0400h	Poponyod	
to 3B FFFFh	Reserved	
3C 0000h		
to	Device Configuration Information (3)(4)(5)	
3C 000Ah	201100 Configuration Information	
3C 000Bh		
to	Reserved	
3F FFFBh		
3F FFFCh		
to	Revision ID (1 Word) ⁽³⁾⁽⁴⁾⁽⁵⁾	
3F FFFDh		
3F FFFEh	(OVA)(E)	
to	Device ID (1 Word) ⁽³⁾⁽⁴⁾⁽⁵⁾	
3F FFFFh		

- **Note 1:** Storage Area Flash is implemented as the last 128 Words of User Flash, if enabled.
 - 2: The addresses do not roll over. The region is read as '0'.
 - **3:** Not code-protected.
 - **4:** Hard-coded in silicon.
 - 5: This region cannot be written by the user and it's not affected by a Bulk Erase.