

BANK 8		BANK 9		BANK 10		BANK 11		BANK 12		BANK 13		BANK 14		BANK 15					
400h	Core Registers	480h	Core Registers	500h	Core Registers	580h	Core Registers	600h	Core Registers	680h	Core Registers	700h	Core Registers	780h	Core Registers				
408h		488h		508h		588h		608h		688h		708h		788h					
40Ch		48Ch		50Ch		58Ch		60Ch		68Ch		70Ch		78Ch					
40Dh		48Dh		50Dh		58Dh		60Dh		68Dh		70Dh		78Dh					
40Eh		48Eh		50Eh		58Eh		60Eh		68Eh		70Eh		78Eh					
40Fh		48Fh		50Fh		58Fh		60Fh		68Fh		70Fh		78Fh					
410h		490h		510h		590h		610h		690h		710h		790h					
411h		491h		511h		591h		611h		691h		711h		791h					
412h		492h		512h		592h		612h		692h		712h		792h					
413h		493h		513h		593h		613h		693h		713h		793h					
414h	494h	514h	594h	614h	694h	714h	794h												
415h	495h	515h	595h	615h	695h	715h	795h												
416h	496h	516h	596h	616h	696h	716h	796h												
417h	497h	517h	597h	617h	697h	717h	797h												
418h	498h	518h	598h	618h	698h	718h	798h												
419h	499h	519h	599h	619h	699h	719h	799h												
41Ah	49Ah	51Ah	59Ah	61Ah	69Ah	71Ah	79Ah												
41Bh	49Bh	51Bh	59Bh	61Bh	69Bh	71Bh	79Bh												
41Ch	49Ch	51Ch	59Ch	61Ch	69Ch	71Ch	79Ch												
41Dh	49Dh	51Dh	59Dh	61Dh	69Dh	71Dh	79Dh												
41Eh	49Eh	51Eh	59Eh	61Eh	69Eh	71Eh	79Eh												
41Fh	49Fh	51Fh	59Fh	61Fh	69Fh	71Fh	79Fh												
420h	General Purpose Registers 80 Bytes ⁽¹⁾	4A0h	General Purpose Registers 80 Bytes ⁽¹⁾	520h	General Purpose Registers 80 Bytes ⁽¹⁾	5A0h	General Purpose Registers 80 Bytes ⁽¹⁾	620h	General Purpose Registers 48 Bytes ⁽¹⁾	Unimplemented Read as '0'	Unimplemented Read as '0'	Unimplemented Read as '0'	Unimplemented Read as '0'	Unimplemented Read as '0'	Unimplemented Read as '0'				
46Fh	Common RAM (Accesses 70h-7Fh)	4EFh	Common RAM (Accesses 70h-7Fh)	56Fh	Common RAM (Accesses 70h-7Fh)	5EFh	Common RAM (Accesses 70h-7Fh)	66Fh	Common RAM (Accesses 70h-7Fh)	6EFh	Common RAM (Accesses 70h-7Fh)	76Fh	Common RAM (Accesses 70h-7Fh)	7EFh	Common RAM (Accesses 70h-7Fh)				
470h		4F0h		570h		5F0h		670h		6F0h		770h		7F0h					
47Fh		4FFh		57Fh		5FFh		67Fh		6FFh		77Fh		7FFh					

Note: 1. Not available on PIC16F13254/74 devices.

Legend:

Unimplemented data memory locations, read as '0'