

BANK 8		BANK 9		BANK 10		BANK 11		BANK 12		BANK 13		BANK 14		BANK 15		
400h	Core Registers	480h	Core Registers	500h	Core Registers	580h	Core Registers	600h	Core Registers	680h	Core Registers	700h	Core Registers	780h	Core Registers	
40Bh		48Bh		50Bh		58Bh		60Bh		68Bh		70Bh		78Bh		
40Ch	—	48Ch	—	50Ch	—	58Ch	—	60Ch	—	68Ch	—	70Ch	PIR0	78Ch	—	
40Dh	—	48Dh	—	50Dh	—	58Dh	—	60Dh	—	68Dh	—	70Dh	PIR1	78Dh	—	
40Eh	—	48Eh	—	50Eh	—	58Eh	—	60Eh	—	68Eh	—	70Eh	PIR2	78Eh	—	
40Fh	—	48Fh	—	50Fh	—	58Fh	—	60Fh	—	68Fh	—	70Fh	—	78Fh	—	
410h	—	490h	—	510h	—	590h	—	610h	—	690h	—	710h	—	790h	—	
411h	—	491h	—	511h	—	591h	—	611h	—	691h	—	711h	—	791h	—	
412h	—	492h	—	512h	—	592h	—	612h	—	692h	—	712h	—	792h	—	
413h	—	493h	—	513h	—	593h	—	613h	—	693h	—	713h	—	793h	—	
414h	—	494h	—	514h	—	594h	—	614h	—	694h	—	714h	—	794h	—	
415h	—	495h	—	515h	—	595h	—	615h	—	695h	—	715h	—	795h	—	
416h	—	496h	—	516h	—	596h	—	616h	—	696h	—	716h	PIE0	796h	—	
417h	—	497h	—	517h	—	597h	—	617h	—	697h	—	717h	PIE1	797h	—	
418h	—	498h	—	518h	—	598h	—	618h	—	698h	—	718h	PIE2	798h	—	
419h	—	499h	—	519h	—	599h	—	619h	—	699h	—	719h	—	799h	—	
41Ah	—	49Ah	—	51Ah	—	59Ah	—	61Ah	—	69Ah	—	71Ah	—	79Ah	—	
41Bh	—	49Bh	—	51Bh	—	59Bh	—	61Bh	—	69Bh	—	71Bh	—	79Bh	—	
41Ch	—	49Ch	—	51Ch	—	59Ch	TMROL	61Ch	—	69Ch	—	71Ch	—	79Ch	—	
41Dh	—	49Dh	—	51Dh	—	59Dh	TRMOH	61Dh	—	69Dh	—	71Dh	—	79Dh	—	
41Eh	—	49Eh	—	51Eh	—	59Eh	TOCON0	61Eh	—	69Eh	—	71Eh	—	79Eh	—	
41Fh	—	49Fh	—	51Fh	—	59Fh	TOCON1	61Fh	—	69Fh	—	71Fh	—	79Fh	—	
420h	General Purpose Registers 80 Bytes ⁽¹⁾	4A0h	General Purpose Registers 80 Bytes ⁽¹⁾	520h	General Purpose Registers 80 Bytes ⁽¹⁾	5A0h	General Purpose Registers 80 Bytes ⁽¹⁾	620h	General Purpose Registers 48 Bytes ⁽¹⁾	Unimplemented Read as '0'	6A0h	Unimplemented Read as '0'	720h	Unimplemented Read as '0'	7A0h	Unimplemented Read as '0'
64Fh		Unimplemented Read as '0'		66Fh		Common RAM (Accesses 70h-7Fh)		76Fh	Common RAM (Accesses 70h-7Fh)							
650h		Unimplemented Read as '0'		67Fh		Common RAM (Accesses 70h-7Fh)		77Fh	Common RAM (Accesses 70h-7Fh)							
66Fh		Common RAM (Accesses 70h-7Fh)		77Fh		Common RAM (Accesses 70h-7Fh)										
67Fh		Common RAM (Accesses 70h-7Fh)		77Fh		Common RAM (Accesses 70h-7Fh)										

Note: 1. PIC16F15255 only

Legend:

Unimplemented data memory locations, read as '0'