


BANK 8		BANK 9		BANK 10		BANK 11		BANK 12		BANK 13		BANK 14		BANK 15									
400h	Core Registers	480h	Core Registers	500h	Core Registers	580h	Core Registers	600h	Core Registers	680h	Core Registers	700h	Core Registers	780h	Core Registers								
40Bh		48Bh		50Bh		58Bh		60Bh		68Bh		70Bh		78Bh									
40Ch	PWM3DCL	48Ch	NCO1ACCL	50Ch	CWG1CLK	58Ch	CLCnCON	60Ch	RC1REG	68Ch	SSP1BUF	70Ch	—	78Ch	—								
40Dh	PWM3DCH	48Dh	NCO1ACCH	50Dh	CWG1ISM	58Dh	CLCnPOL	60Dh	TX1REG	68Dh	SSP1ADD	70Dh	—	78Dh	—								
40Eh	PWM3CON	48Eh	NCO1ACCU	50Eh	CWG1DBR	58Eh	CLCnSELO	60Eh	SP1BRGL	68Eh	SSP1MSK	70Eh	—	78Eh	—								
40Fh	PWM4DCL	48Fh	NCO1INCL	50Fh	CWG1DBF	58Fh	CLCnSEL1	60Fh	SP1BRGH	68Fh	SSP1STAT	70Fh	—	78Fh	—								
410h	PWM4DCH	490h	NCO1INCH	510h	CWG1CON0	590h	CLCnSEL2	610h	RC1STA	690h	SSP1CON1	710h	—	790h	—								
411h	PWM4CON	491h	NCO1INCU	511h	CWG1CON1	591h	CLCnSEL3	611h	TX1STA	691h	SSP1CON2	711h	—	791h	—								
412h	PWM5DCL	492h	NCO1CON	512h	CWG1AS0	592h	CLCnGLS0	612h	BAUD1CON	692h	SSP1CON3	712h	—	792h	—								
413h	PWM5DCH	493h	NCO1CLK	513h	CWG1AS1	593h	CLCnGLS1	613h	—	693h	—	713h	—	793h	—								
414h	PWM5CON	494h	—	514h	CWG1STR	594h	CLCnGLS2	614h	—	694h	—	714h	—	794h	—								
415h	—	495h	—	515h	—	595h	CLCnGLS3	615h	—	695h	—	715h	—	795h	—								
416h	—	496h	—	516h	—	596h	CLCSELECT	616h	RC2REG	696h	SSP2BUF	716h	—	796h	—								
417h	—	497h	—	517h	—	597h	CLCDATA	617h	TX2REG	697h	SSP2ADD	717h	—	797h	—								
418h	—	498h	—	518h	—	598h	—	618h	SP2BRGL	698h	SSP2MSK	718h	—	798h	—								
419h	—	499h	—	519h	—	599h	—	619h	SP2BRGH	699h	SSP2STAT	719h	—	799h	—								
41Ah	—	49Ah	—	51Ah	—	59Ah	—	61Ah	RC2STA	69Ah	SSP2CON1	71Ah	—	79Ah	—								
41Bh	—	49Bh	—	51Bh	—	59Bh	—	61Bh	TX2STA	69Bh	SSP2CON2	71Bh	—	79Bh	—								
41Ch	—	49Ch	—	51Ch	—	59Ch	—	61Ch	BAUD2CON	69Ch	SSP2CON3	71Ch	—	79Ch	—								
41Dh	—	49Dh	—	51Dh	—	59Dh	—	61Dh	—	69Dh	—	71Dh	—	79Dh	—								
41Eh	—	49Eh	—	51Eh	—	59Eh	—	61Eh	—	69Eh	—	71Eh	—	79Eh	—								
41Fh	PWMTMR50	49Fh	—	51Fh	—	59Fh	—	61Fh	—	69Fh	—	71Fh	—	79Fh	—								
420h	General Purpose Registers 80 Bytes ⁽¹⁾	4A0h	General Purpose Registers 80 Bytes ⁽¹⁾	520h	General Purpose Registers 80 Bytes ⁽¹⁾	5A0h	General Purpose Registers 80 Bytes ⁽¹⁾	620h	General Purpose Registers 48 Bytes ⁽¹⁾	Unimplemented Read as '0'	6A0h	Unimplemented Read as '0'	720h	Unimplemented Read as '0'	7A0h	Unimplemented Read as '0'							
64Fh		Unimplemented Read as '0'		66Fh		Unimplemented Read as '0'		68Fh	Unimplemented Read as '0'		70Fh		Unimplemented Read as '0'		72Fh		Unimplemented Read as '0'	74Fh	Unimplemented Read as '0'	76Fh	Unimplemented Read as '0'	78Fh	Unimplemented Read as '0'
66Fh		Unimplemented Read as '0'		68Fh		Unimplemented Read as '0'		70Fh	Unimplemented Read as '0'		72Fh		Unimplemented Read as '0'		74Fh		Unimplemented Read as '0'	76Fh	Unimplemented Read as '0'	78Fh	Unimplemented Read as '0'	80Fh	Unimplemented Read as '0'
68Fh		Unimplemented Read as '0'		70Fh		Unimplemented Read as '0'		72Fh	Unimplemented Read as '0'		74Fh		Unimplemented Read as '0'		76Fh		Unimplemented Read as '0'	78Fh	Unimplemented Read as '0'	80Fh	Unimplemented Read as '0'	82Fh	Unimplemented Read as '0'
6A0h		Unimplemented Read as '0'		720h		Unimplemented Read as '0'		740h	Unimplemented Read as '0'		760h		Unimplemented Read as '0'		780h		Unimplemented Read as '0'	800h	Unimplemented Read as '0'	820h	Unimplemented Read as '0'	840h	Unimplemented Read as '0'
46Fh	Common RAM (Accesses 70h-7Fh)	4EFh	Common RAM (Accesses 70h-7Fh)	56Fh	Common RAM (Accesses 70h-7Fh)	5EFh	Common RAM (Accesses 70h-7Fh)	66Fh	Common RAM (Accesses 70h-7Fh)	6EFh	Common RAM (Accesses 70h-7Fh)	76Fh	Common RAM (Accesses 70h-7Fh)	7EFh	Common RAM (Accesses 70h-7Fh)								
470h		Common RAM (Accesses 70h-7Fh)		4F0h		Common RAM (Accesses 70h-7Fh)		570h		Common RAM (Accesses 70h-7Fh)		5F0h		Common RAM (Accesses 70h-7Fh)		670h	Common RAM (Accesses 70h-7Fh)	770h	Common RAM (Accesses 70h-7Fh)	7F0h	Common RAM (Accesses 70h-7Fh)		
47Fh		Common RAM (Accesses 70h-7Fh)		4FFh		Common RAM (Accesses 70h-7Fh)		57Fh		Common RAM (Accesses 70h-7Fh)		5FFh		Common RAM (Accesses 70h-7Fh)		67Fh	Common RAM (Accesses 70h-7Fh)	77Fh	Common RAM (Accesses 70h-7Fh)	7FFh	Common RAM (Accesses 70h-7Fh)		

Note: 1. Not available on PIC16F18044

Legend:

 Unimplemented data memory locations, read as '0'