

Steps

1. Choose Project
2. Select Device
3. Select Header
4. Select Plugin Board
5. Select Compiler
- 6. Select Project Name and Folder**
7. (Optional) Add Project

**Select Project Name and Folder**

Project Name:

getting_started_pic32cm_jh01_cpro

Project Location:

C:\microchip\h3\Technical_Brief

Browse...

Project Folder:

\Technical_Brief\getting_started_pic32cm_jh01_cpro.X

- ☐ Overwrite existing project.
- ☐ Also delete sources.
- ☒ Set as main project
- ☒ Open MCC on Finish
- ☐ Use project location as the project folder

Encoding:

ISO-8859-1

< Back

Add Another Project

Next >

Finish

Cancel

Help