


BANK 8		BANK 9		BANK 10		BANK 11		BANK 12		BANK 13		BANK 14		BANK 15	
400h	Core Registers	480h	Core Registers	500h	Core Registers	580h	Core Registers	600h	Core Registers	680h	Core Registers	700h	Core Registers	780h	Core Registers
40Bh		48Bh		50Bh		58Bh		60Bh		68Bh		70Bh		78Bh	
40Ch	CCPR1L	48Ch	PWM1ERS	50Ch	CLBICON	58Ch	PWM2ERS	60Ch	—	68Ch	CLCnCON	70Ch	RC1REG	78Ch	SSP1BUF
40Dh	CCPR1H	48Dh	PWM1CLK	50Dh	CLBSWINU	58Dh	PWM2CLK	60Dh	—	68Dh	CLCnPOL	70Dh	TX1REG	78Dh	SSP1ADD
40Eh	CCP1CON	48Eh	PWM1LDS	50Eh	CLBSWINH	58Eh	PWM2LDS	60Eh	—	68Eh	CLCnSELO	70Eh	SP1GRBL	78Eh	SSP1MSK
40Fh	CCP1CAP	48Fh	PWM1PRL	50Fh	CLBSWINM	58Fh	PWM2PRL	60Fh	—	68Fh	CLCnSEL1	70Fh	SP1BRGH	78Fh	SSP1STAT
410h	CCPR2L	490h	PWM1PRH	510h	CLBSWINL	590h	PWM2PRH	610h	—	690h	CLCnSEL2	710h	RC1STA	790h	SSP1CON1
411h	CCPR2H	491h	PWM1CPRE	511h	—	591h	PWM2CPRE	611h	—	691h	CLCnSEL3	711h	TX1STA	791h	SSP1CON2
412h	CCP2CON	492h	PWM1PIPOS	512h	—	592h	PWM2PIPOS	612h	—	692h	CLCnGLS0	712h	BAUD1CON	792h	SSP1CON3
413h	CCP2CAP	493h	PWM1GIR	513h	—	593h	PWM2GIR	613h	—	693h	CLCnGLS1	713h	—	793h	—
414h	—	494h	PWM1GIE	514h	—	594h	PWM2GIE	614h	—	694h	CLCnGLS2	714h	—	794h	—
415h	—	495h	PWM1CON	515h	CLBCLK	595h	PWM2CON	615h	—	695h	CLCnGLS3	715h	—	795h	—
416h	—	496h	PWM1S1CFG	516h	CLBSWOUTH	596h	PWM2S1CFG	616h	—	696h	CLCSELECT	716h	RC2REG	796h	—
417h	—	497h	PWM1S1P1L	517h	CLBSWOUTL	597h	PWM2S1P1L	617h	—	697h	CLCDATA	717h	TX2REG	797h	—
418h	—	498h	PWM1S1P1H	518h	CLBDEBUG0	598h	PWM2S1P1H	618h	—	698h	—	718h	SP2GRBL	798h	—
419h	—	499h	PWM1S1P2L	519h	—	599h	PWM2S1P2L	619h	—	699h	—	719h	SP2BRGH	799h	—
41Ah	—	49Ah	PWM1S1P2H	51Ah	—	59Ah	PWM2S1P2H	61Ah	—	69Ah	—	71Ah	RC2STA	79Ah	—
41Bh	—	49Bh	—	51Bh	—	59Bh	—	61Bh	—	69Bh	—	71Bh	TX2STA	79Bh	—
41Ch	—	49Ch	—	51Ch	—	59Ch	—	61Ch	—	69Ch	—	71Ch	BAUD2CON	79Ch	—
41Dh	—	49Dh	—	51Dh	—	59Dh	—	61Dh	—	69Dh	—	71Dh	—	79Dh	—
41Eh	—	49Eh	PWMLOAD	51Eh	—	59Eh	—	61Eh	—	69Eh	—	71Eh	—	79Eh	—
41Fh	CCPTMRS0	49Fh	PWMEN	51Fh	—	59Fh	—	61Fh	—	69Fh	—	71Fh	—	79Fh	—
420h	General Purpose Registers 80 Bytes	4A0h	General Purpose Registers 80 Bytes	520h	General Purpose Registers 80 Bytes	5A0h	General Purpose Registers 80 Bytes	620h	General Purpose Registers 80 Bytes	6A0h	General Purpose Registers 80 Bytes	7A0h	General Purpose Registers 80 Bytes	8A0h	General Purpose Registers 80 Bytes
46Fh		4EFh		56Fh		5EFh		66Fh		6EFh		76Fh		86Fh	
470h	Common RAM (Accesses 70h-7Fh)	4F0h	Common RAM (Accesses 70h-7Fh)	570h	Common RAM (Accesses 70h-7Fh)	5F0h	Common RAM (Accesses 70h-7Fh)	670h	Common RAM (Accesses 70h-7Fh)	6F0h	Common RAM (Accesses 70h-7Fh)	770h	Common RAM (Accesses 70h-7Fh)	870h	Common RAM (Accesses 70h-7Fh)
47Fh		4Fh		57Fh		5Fh		67Fh		6Fh		77Fh		87Fh	

Legend:

 Unimplemented data memory locations, read as '0'